

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE
APPLICATION FOR UNITED STATES PATENT

Title: **SEMI-PERMANENT CANAL HEARING DEVICE**

Inventors: **ADNAN SHENNIB**
Fremont, California

RICHARD C. URSO
Redwood City, California

DIEP H. NGO
San Jose, California

Assignee: **INSONUS MEDICAL, INC.**
Hayward, California

0919696-11208

SEMI-PERMANENT CANAL HEARING DEVICE

Cross-Reference to Related Applications

5 This application is related to co-pending patent applications Serial No. 09/181,533, filed October 28, 1998, titled "Remote Magnetic Activation of Hearing Devices" (referred to herein as the "533 application"), and Serial No. 09/190,764, filed November 12, 1998, titled "Battery Enclosure for Canal Hearing Devices" (referred to herein as the "764 application").

Background of the Invention

a. Technical Field

10 The present invention relates to hearing devices, and, more particularly, to hearing devices that are semi-permanently positioned in the ear canal for improved energy efficiency, sound fidelity, and inconspicuous wear.

b. Description of the Prior Art

(1) Brief Description of Ear Canal Anatomy and Physiology

15 The external acoustic meatus (ear canal) is generally narrow and tortuous as shown in the coronal view in FIG. 1. The ear canal 10 is approximately 23-29 millimeters (mm) long from the canal aperture 17 to the tympanic membrane 18 (eardrum). The lateral part, a cartilaginous region 11, is relatively soft due to the underlying cartilaginous tissue. The cartilaginous region 11 of the ear canal 10 deforms and moves in response to the mandibular
20 (jaw) motions, which occur during talking, yawning, eating, etc. Hair 12 is primarily present

in the cartilaginous region. The medial part, a bony region 13 proximal to the tympanic membrane, is rigid due to the underlying bony tissue. The skin 14 in the bony region 13 is thin (relative to the skin 16 in the cartilaginous region) and is sensitive to touch or pressure. A characteristic bend 15 roughly occurring at the bony-cartilaginous junction 19 separates the cartilaginous and bony regions 11 and 13, respectively. The magnitude of this bend varies significantly among individuals.

A cross-sectional view of the typical ear canal 10 (FIG. 2) reveals generally an oval shape with a long diameter D_L in the vertical axis and a short diameter D_s in the horizontal axis. Canal dimensions vary significantly among individuals as shown below in the section titled Experiment-A. The long/short ratio (D_L/D_s) ranges from 1:1 to 2:1. The diameter ranges from as little as 4 mm (D_s in the bony region 13 in small canals) to as much as 12 mm (D_L in the cartilaginous region 11 in large canals).

Physiological debris 4 in the ear canal is primarily produced in the cartilaginous region 11, and includes cerumen (earwax), sweat, and oils produced by the various glands underneath the skin in the lateral portion of the cartilaginous region. Cerumen is naturally extruded from the ear canal by the process of lateral epithelial cell migration (see, e.g., Ballachanda, *The Human Ear Canal*, Singular Publishing, 1950, pp. 195). There is no cerumen production or hair 12 in the bony part of the ear canal. The ear canal 10 terminates medially with the tympanic membrane 18. Externally and lateral to the ear canal are the concha cavity 2 and the auricle 3.

Several types of hearing losses affect millions of individuals. Hearing loss

naturally occurs beginning at higher frequencies (4000 Hz and above) and increasingly spreads to lower frequencies with age.

(2) The Limitations of Conventional Canal Hearing Devices.

Conventional hearing devices that fit in the ear of individuals generally fall into one of 4 categories as classified by the hearing aid industry: (1) the Behind-The-Ear (BTE) type which, as the designation indicates, is worn behind the ear and is attached to an ear mold which fit mostly in the concha; (2) the In-The-Ear (ITE) type which fits largely in the auricle and concha areas, extending minimally into the ear canal; (3) the In-The-canal (ITC) type which fits largely in the concha area and extends into the ear canal (see, e.g., Valente M., *Strategies for Selecting and Verifying Hearing Aid Fittings*, Thieme Medical Publishing, pp. 255-256, 1994), and (4) the Completely-In-the-Canal (CIC) type which fits completely within the ear canal past the aperture (see, e.g., Chasin, M. *CIC Handbook*, Singular Publishing, 1997 (referred to hereinafter as "*Chasin*"), p. 5).

The continuous trend for the miniaturization of hearing aids is fueled by the demand for *invisible* hearing products in order to alleviate the social stigma associating hearing loss with aging and disability. In addition to the cosmetic advantage of a CIC device (FIG. 3), there are actual acoustic benefits resulting from the deep placement of the device within the ear canal. These benefits include improved high frequency response, less distortion, reduction of feedback and improved telephone use (e.g., *Chasin*, pp. 10-11).

However, even with these significant advances leading to the advent of CIC technology, there remain a number of fundamental limitations associated with the underlying

design and configurations of conventional CIC technology. They include: (a) frequent device handling, (b) acoustic feedback, (c) custom manufacturing & impression taking, (d) limited energy efficiency, (e) size limitation due to space inefficiency of enclosure, and (f) occlusion related problems. These limitations are discussed in more detail below.

5 (a) Frequent device handling:

Conventional CIC devices require frequent insertion and removal from the ear canal. Manufacturers often recommend daily removal for cleaning and maintenance of the CIC device (see, e.g., *Users's Instructions, SENSO CIC and Mini Canal*, Widex Hearing Aid Co. Feb. 97, pp. 11, 16; and *General Information for Hearing aid Users*, Siemens Hearing Instruments, Inc. Mar. 98, p. 8). Frequent removal of conventional CICs is also required for relieving the ear from the pressures of the device occluding the cartilaginous region. Furthermore, CIC hearing aid removal is also required in order to replace its battery, typically lasting from 1 to 2 weeks. The manual dexterity required to handle a CIC hearing device frequently poses a serious challenge to the many hearing impaired persons represented by the elderly. These individuals typically suffer from arthritis, tremors, or other neurologic problems that limit their ability to handle a miniature hearing aid.

(b) Acoustic feedback:

Acoustic feedback occurs when a portion of the sound output, typically from a receiver (speaker), leaks to the input of a sound system such as a microphone of a hearing aid. This leakage often causes a sustained oscillation, which is manifested by “whistling” or “squealing”. Feedback is not only annoying to hearing aid users but also

interferes with their communication. Feedback is typically alleviated by occluding (sealing) the ear canal tightly, particularly at the cartilaginous region 11, as illustrated with the CIC hearing device in FIG. 3.

(c) Custom manufacturing & impression taking:

Conventional CIC devices are custom made according to an impression taken from the ear of the individual. The device housing 22 (FIG. 3), known as a *shell*, is custom fabricated according to the impression, to accurately assume the shape of the individual ear canal. Customizing a conventional CIC is required in order to minimize feedback and to improve comfort of wear. But custom manufacturing is time consuming and results in considerable cost overhead for the manufacturer, ultimately reflected in the price of the CIC device to the consumer (user). Furthermore, impression taking is often uncomfortable for the user.

(d) Limited energy efficiency:

The efficiency of a hearing device is generally inversely proportional to the distance or residual volume 25 (FIG. 3) between the receiver (speaker) end 23 and the tympanic membrane 18; the closer the receiver is to the tympanic membrane, the less air mass there is to vibrate, and thus, less energy is required. However, due to concerns related to discomfort and difficulty of insertion, CIC products are typically tapered at their medial end 23 (e.g., *Chasin*, pp. 9-10) and relatively shallow in their placement in order to avoid substantial contact with the bony portion of the ear canal as shown in FIG. 3.

(e) Size limitation due to space inefficiency of enclosure:

Since a conventional CIC is frequently handled by a wearer, the enclosure 22 (FIG. 3) must be made durably thick in order to protect the components contained within (battery 26, microphone 27, amplifier 28 and receiver 29). Therefore, a shell, or main housing, is typically made of rigid material such as plastic (e.g. acrylic). Typical thickness for this housing or enclosure of CIC devices is 0.5 to 0.7 mm, which adds considerable dimensions to the conventional CIC. Furthermore, conventional shells enclose the battery along with other components, which makes the overall housing large. This space inefficiency renders the device unsuitable for many individuals with small or highly contoured ear canals who would not be able to comfortably tolerate insertion and wear of a CIC device deep in the ear canal.

(f) Occlusion related problems:

(i) Discomfort, irritation and even pain may occur due to canal abrasion caused by frequent insertion and removal of a CIC hearing aid. A removal strand 24 (FIG. 3) is generally provided with CIC devices to assist the wearer in the daily removal process. Due to the resultant discomfort and abrasion, hearing devices are frequently returned to the manufacture for improvement of the custom fit and comfort (e.g., *Chasin*, p. 44). "The long term effects of the hearing aid are generally known, and consist of atrophy of the skin and a gradual remodeling of the bony canal. Chronic pressure on the skin lining the ear canal causes a thinning of this layer, possibly with some loss of skin appendages" (*Chasin*, p. 58).

(ii) Moisture produced in the cartilaginous ear canal causes

damage to the ear canal and the hearing device therein. "The humidity in the occluded portion of the canal increases rapidly. This is worse during hot and humid weather, following exercise" (*Chasin*, pp. 57-58). It is often recommended that the CIC device should be removed from the ear canal daily to reduce the damaging effects of moisture in the canal.

5 (iii) Cerumen *impaction* (blockage of the ear canal by earwax) may occur when cerumen, produced in the cartilaginous region, is pushed and accumulated deeper in the bony region of ear canal by the frequent insertion of a CIC hearing device (e.g., *Chasin*, p. 27, pp. 56-57). Cerumen can also build up on the receiver of the hearing device causing frequent malfunction. Cerumen contamination due to frequent insertion is probably the most common factor leading to hearing aid damage and repair (see, e.g., Oliveira, et al, *The Wax Problem: Two New Approaches*, *The Hearing Journal*, Vol. 46, No. 8).

10 (iv) The *occlusion effect*, a common acoustic problem attributable to occlusion of the ear canal by the hearing device, is manifested by the perception of the user's (wearer's) own voice ("self-voice") being loud and unnatural compared to that with an open (unoccluded) ear canal. This phenomenon is sometimes referred to as the "barrel effect", since it resembles the experience of talking into a barrel. The *occlusion effect*, which may be experienced by plugging the ears with fingers while talking, is generally related to self-voice resonating within the ear canal. For hearing aid users, the *occlusion effect* is inversely proportional to the residual volume 25 (FIG. 3) of air between the occluding hearing device and the tympanic membrane. Therefore, the *occlusion effect* is considerably alleviated by deeper placement of the device in the ear canal. Incorporating a vent 21 across the CIC

hearing device 20 can also alleviate this effect.

The above limitations in conventional CIC devices are highly interrelated. For example, when a CIC is worn in the ear canal, movements in the cartilaginous region “can lead to slit leaks that lead to feedback, discomfort, the occlusion effect, and ‘pushing’ of the aid from the ear” (*Chasin*, pp. 12-14). The relationship between the limitations is often adverse. For example, occluding the ear canal tightly is desired on one hand to prevent feedback. On the other hand, however, tight occlusion leads to various adverse side effects as mentioned above. Attempts to alleviate the occlusion effect by a vent 21 provide an opportunistic pathway for leakage and feedback. For this reason, the vent 21 diameter is typically limited in CIC devices to 0.6 - 0.8 mm (e.g., *Chasin*, pp. 27-28).

(3) Review of state-of-the-art in related hearing device technology

Ahlberg et al and Oliviera et al in U.S. Patent Nos. (USPNs) 4,880,076 and 5,002,151 respectively, disclose a compressible polymeric foam assembly attached to an earpiece of a hearing device. The compressible foam assembly (Fig. 1 of both Ahlberg and Oliviera) is inserted in to the ear canal to couple sound and seal acoustically therein. The foam seal is attached serially to the earpiece, which adds a considerable dimension to overall length of the hearing device. Therefore, the application of such compressible foam assembly is limited to BTE and ITE devices which have housings positioned external to the ear canal.

Cirillo in USPN 4,830,139 discloses means for holding a speaker mold (16 in Cirillo's Fig. 1) in the ear canal via a sealant made of flexible gelatinous water-soluble material. The mold is attached to a wire (18) extending to the outside of the ear canal, and therefore,

Cirillo's proposal is presumably also for hearing devices that are positioned outside the ear canal. It does not deal with devices that are completely positioned in the ear canal. Furthermore, since the sealant is water-soluble, it can also be assumed to be suitable only for short-term use as it will deteriorate with moisture exposure (e.g., as will occur when the wearer is taking a shower or is caught in the rain).

Sauer et al in USPN 5,654,530 disclose an insert associated with an ITE device (Sauer's Fig. 1) or a BTE device (Sauer's Fig. 2). The insert is stated to be a "sealing and mounting element" made of "soft elastic material having slotted outer circumference divided into a plurality of fan-like circumferential segments". The sealing element is positioned at the lateral portion of the ear canal as shown in Sauer's figures. According to the patent, the insert is for ITEs and BTEs only, not for inconspicuous hearing devices that are deeply and completely inserted in the ear canal. The insert as disclosed is used in the cartilaginous area, thus occluding the ear canal in the region of hair, cerumen and sweat production. Clearly, long term use (without daily removal) will interfere in the natural production of physiologic debris.

Garcia et al. in USPN 5,742,692 disclose a hearing device (10 in Garcia's Fig. 1) attached to a flexible seal 30 which is fitted in the bony region of the ear canal. The device 10 comprises hearing aid components (i.e., microphone 12, receiver 15 and battery 16, etc., as shown by Garcia) which are contained within a single "unitary" housing 20. The device 10 is not likely to fit deeply and comfortably in many small and contoured canals due to the space inefficiency associated with the unitary housing 20. In addition to the size disadvantage, the device 10 occludes the ear canal in the cartilaginous region as shown in Garcia's Fig. 2.

Henneberger and Biermans in USPNs 4,680,799 and 4,937,876, respectively, also disclose hearing aids with conventional housings, which occlude the ear canal and comprise a unitary enclosure for microphone, battery and receiver components therein.

Weiss et al. in USPNs 3,783,201 and 3,865,998 disclose an alternate hearing device configuration which fits partially in the ear canal (Fig. 1 in both the Weiss '201 and '998 patents) with a separate microphone 14 and receiver 18. The main housing, enclosing battery and amplifier, is designed to fit in the concha area outside the ear canal as shown. The microphone 14 is positioned in the pinna completely outside the ear canal. The device is clearly visible to the casual observer.

Geib in USPN 3,527,901 discloses a hearing device with housing made of soft resilient material, which encloses the entire body of the device. This approach eliminates conventional rigid enclosures, and is presumably more comfortable to wear. However, the unitary flexible enclosure provides no improvement in space efficiency and also poses serious concerns regarding the reliability of interconnects, and of the device in general, during frequent handling. The disclosed hearing device was not designed to fit entirely in the ear canal, Geib stating that "the hearing aid makes a much better fit within the concha and ear canal of the user thereby providing a more effective seal and reducing the problems of direct acoustic feedback" (col 2, lines 40-43).

Hardt in USPN 4,607,720 discloses a hearing device which is mass-producible with a soft sealing plug that is serially attached to the receiver. Although the problem of custom manufacturing is addressed, the unitary enclosure (containing major hearing aid

components; battery, microphone and receiver) is, as with other prior art proposals, space-inefficient for deep canal fittings.

Voroba et al in USPN 4,870,688 also disclose a mass-producible hearing aid, which includes a solid shell core (20 in Veroba's Figs. 1 and 2) with a flexible covering 30 affixed to its exterior. Similarly, the rigid core represents a unitary enclosure for all major hearing aid components, and thus, is space-inefficient for deep canal fittings.

Hartl et al. in USPN 4,639,556 disclose a hearing aid with a flexible printed circuit board attached to a face-plate. The flexible circuit board and major hearing aid components are also enclosed in a unitary housing (1 in Hartl's Fig. 1). Similarly, this leads to a space-inefficient design for deep canal fittings.

McCarrel et al, Martin, Geib et al, and Adelman, in USPNs 3,061,689, RE 26,258, 3,414,685 and 5,390,254, respectively, disclose miniature hearing devices with a receiver portion flexibly separate from a main part. The receiver portion insertable into the ear canal with the main part occupying the concha (McCarrel's Fig. 2, Geib's Fig 10, and Adelman's Fig. 3B). This placement facilitates access to the device for insertion and removal. In each of these disclosures, the aforementioned main part contains all the major components of the hearing device, including among others the battery, amplifier and microphone, except the receiver. Therefore, this main part is not sufficiently space-efficient to fit past the aperture of the ear canal for most individuals.

Shennib et al in USPN 5,701,348 disclose an articulated hearing device with flexibly connecting modules, stating that "the main module 12 includes all of the typical

components found in hearing devices, except for the receiver" (col. 6, lines 64-66). The main module includes a battery 16, a battery compartment 15, circuit 17 (amplifier) and microphone 14. Because of its articulated design and assorted soft acoustic seal 43, the hearing device disclosed by Shennib is suitable to fit a variety of ear canals without resorting to custom manufacturing, and thus can be mass-producible as disclosed. Although a CIC configuration is disclosed (see Shennib's Fig. 23), the depth of insertion, particularly for small and contoured ear canals, is severely limited by the design of the main module 12 which contains the power source (battery) along with other major components (e.g., the microphone). Furthermore, in each of its disclosed configurations, the device substantially occludes the ear canal in the cartilaginous region, which would interfere with hair and the natural production of physiologic debris. In addition, the disclosed CIC configuration is designed for insertion and removal by a wearer with good dexterity (col. 11, lines 18-20). Therefore, the disclosed CIC device would be unsuitable for continuous long-term use in the ear canal, particularly for persons lacking such dexterity.

It is the principal objective of the present invention to provide a highly space-efficient hearing device, which is suitable to be completely positioned in the ear canal.

Another objective is to provide a design for a hearing device which is mass-producible, and which requires neither custom manufacture nor the taking of individual ear canal impressions.

A further objective of the invention is to provide a hearing device which occludingly seals the ear canal in the bony region, but not at the cartilaginous region, and thus

does not interfere with hair and the natural production and elimination of physiologic debris in the ear canal.

Yet another objective is to provide a semi-permanent hearing device which is inserted by a physician, or by other professionals under the supervision of a physician, for long-term use in the ear canal.

Semi-permanent, or alternatively long-term use, is defined herein as continuous placement and use of the hearing device within the ear canal without any removal, daily or otherwise, for at least a month.

Summary of the Invention

The invention provides a semi-permanent hearing device which is completely positioned within the ear canal of an individual for long-term use. The device comprises a sealing retainer substantially positioned in the bony region of the ear canal and a core assembly comprising a receiver assembly coaxially positioned within the sealing retainer.

The core assembly extends from the sealing retainer to the cartilaginous region in a non-occluding fashion, thus minimizing interference with hair and earwax production present in the cartilaginous part of the ear canal. In a preferred embodiment of the invention, the core assembly includes a battery assembly including a battery and a thin enclosure having substantially the shape and dimensions of the battery which is encapsulated therein. A connector having the shape of thin ribbon film provides electrical and flexible mechanical connectivity between the receiver assembly, centrally positioned battery assembly, and

microphone assembly positioned in the cartilaginous region. The invention is characterized by the absence of a unitary enclosure or main housing which typically encloses the battery and other components in prior art hearing device designs.

5 In the preferred embodiment, the hearing device is mass-producible and accommodates a variety of canal shapes and sizes without need for custom manufacturing or canal impressions. This desirable objective is accomplished by virtue of the flexibility of the universal core assembly and conformity of the assorted sealing retainer.

The hearing device of the invention is preferably inserted by a physician, or by another professional under the supervision of a physician, for placement entirely within the ear canal and exceptionally close to the eardrum. The space and energy efficient design allows for a comfortable continuous use within the ear canal for extended periods of time, exceeding one month, without the requirement of daily removal as with conventional CICs. In the preferred embodiments, the device is remotely switched on/off by a remote control for optionally conserving the battery energy while the device remains in the ear canal during sleep or non-use.

The invention eliminates the need for manual insertion and removal by the wearer and is therefore particularly suited for hearing impaired persons of poor manual dexterity.

Brief Description of the Drawings:

The above and still further objectives, features, aspects and attendant advantages of the present invention will become apparent from the following detailed description of certain preferred and alternate embodiments and method of manufacture and use thereof constituting the best mode presently contemplated of practicing the invention, when taken in conjunction with the accompanying drawings, in which:

FIG. 1 is a side view of the external ear canal, described above;

FIG. 2 is a cross-sectional view of the ear canal at the bony-cartilaginous junction for (a) small canal, (b) average size canal and (c) large canal, showing the relative dimensions of standard button cell hearing aid batteries, sizes 10A and 312;

FIG. 3 is a side view of the ear canal occluded by a conventional CIC hearing aid positioned therein, described above;

FIG. 4 is a side view of the ear canal showing an embodiment of the semi-permanent canal device of the present invention positioned completely therein, in which the cartilaginous region is unoccluded and the bony region is occluded with a sealing retainer;

FIG. 5 is a detailed side view of the semi-permanent canal device of **FIG. 4**, further illustrating replaceable debris guards for the microphone and receiver;

FIGS. 6a and 6b are cross-sectional views of the ear canal showing the non-occlusive microphone assembly of an embodiment of the canal device of the present invention positioned in the cartilaginous region, providing substantial air-space and no contact with the walls of the ear canal (**FIG. 6a**), and substantial air-space and minimal contact with the walls

or physiologic debris of the ear canal (**FIG. 6b**);

FIGS. 7a and 7b are cross-sectional views of the ear canal showing the receiver assembly and sealing retainer of an embodiment of the canal device of the invention positioned in the bony region with occlusion thereof (**FIG. 7a**), and with venting incorporated in the sealing retainer (**FIG. 7b**);

FIG. 8 is an electrical schematic diagram of a prototype embodiment of the canal device of the invention;

FIG. 9 is a graph of the acoustic response of the prototype embodiment of **FIG. 8** showing the acoustic effect with and without the moisture-proof debris guards placed on the microphone and the receiver of the prototype embodiment;

FIG. 10 is a detailed exploded side view of the flexible connector, battery, microphone and receiver parts of an embodiment of the canal device of the present invention, showing the parts unassembled;

FIG. 11 is a cross-sectional view of the ear canal showing the battery assembly of an embodiment of the canal device of the invention positioned therein, with flexible connector, battery and battery enclosure;

FIG. 12 is a side view of the ear canal showing a programmable embodiment of the canal device of the invention positioned in the ear canal with sealing retainer extending substantially over the battery, and also illustrating a probe tube system with probe tube and external amplifier according to the invention;

FIG. 13 is a side view of the ear canal showing an embodiment of the canal device of the invention positioned in the ear canal with a latchable magnetic switch and an external control magnet;

FIG. 14a is a detailed view of a moisture-proof debris guard in the form of an adhesive pad showing the adhesive layer and receiver sound port for an embodiment of the canal device of the invention; and **FIG. 14b** is a perspective view of the moisture-proof adhesive pad of **FIG. 14a** showing the adhesive layer and adhesive-free area;

FIG. 15 is a side view of the ear canal showing an alternate embodiment of the canal device of the invention positioned entirely in the ear canal and substantially in the bony region thereof;

FIGS. 16a and **16b** are perspective views of a preferred embodiment of the sealing retainer of the canal device, taken respectively from the side (**FIG. 16a**) and from the lateral end (**FIG. 16b**), showing a lateral cavity which partially accommodates the battery assembly indicated by the dotted circle; and

FIG. 17 is a side view of the ear canal showing the central location of the three regions representing the cartilaginous region (C), the bony-cartilaginous junction region (J) and the bony region (B).

Detailed Description of the Preferred Embodiments and Methods of the Invention

5 The present invention provides a semi-permanent hearing device which is adapted to be entirely positioned in the ear canal for long term use. For the sake of additional clarity and understanding in the ensuing detailed description, the disclosures of the aforementioned related co-pending '533 application and '764 application (see section titled "Cross-Reference to Related Applications", above) are incorporated herein by reference.

10 The canal hearing device 30 of the invention will be described with reference to FIGS. 4-16, in which the same reference numbers are used throughout to indicate elements which are common to the several Figures. Hearing device 30 generally comprises a core assembly 35 and a sealing retainer 70 constructed and adapted to be positioned substantially in the bony region 13 of the ear canal. The core assembly 35 includes a receiver (speaker) assembly 60, which is coaxially positioned within the sealing retainer 70.

15 The core assembly 35 extends to the cartilaginous region 11 in a non-occluding fashion, thus minimizing interference with hair and earwax production present in the cartilaginous part of the ear canal 10. The core assembly 35 also includes a battery assembly 50 having a shape and dimensions substantially equivalent to those of the enclosed battery 51, recognizing that battery assembly 50 has a slightly larger size to accommodate snug enclosure of the battery 51 therein. A connector 53, in the shape of thin circuit film or ribbon cable, provides electrical and mechanical connectivity between the receiver assembly 60, the battery assembly 50, and a microphone assembly 40, the latter being positioned in the cartilaginous region 11 when the hearing device is fully inserted and seated in the ear canal for normal use.

The connector **53** is enclosed within the thin enclosure **52** of the battery assembly **50** and extends to the microphone assembly **40** and receiver assembly **60** for connection thereto.

In a preferred embodiment, shown in **FIGS. 4-7**, the sealing retainer **70** is adapted to be positioned, as shown, substantially in the bony region **13** concentrically or coaxially over the receiver assembly **60**. The sealing retainer **70** is configured to provide the primary support for the device **30** within the ear canal **10**. To that end, sealing retainer **70** substantially conforms to the shape of walls **14** of the ear canal in the bony region **13** and retains the device securely within the ear canal **10**. The microphone assembly **40**, including a microphone **43** therein, is non-occludingly positioned in the cartilaginous region **11** with little or no contact with the walls of the ear canal, thus allowing for a substantial air space **49** therebetween as shown in **FIGS. 4, 6a** and **6b**. This minimal contact of the microphone assembly **40** allows for natural production and lateral migration of cerumen (earwax) and other debris in the cartilaginous region **11**. The receiver assembly **60**, in contrast, occludes the ear canal in the bony region **13** via the associated sealing retainer **70**, as shown in **FIG. 7**.

The microphone assembly **40**, battery assembly **50**, and receiver assembly **60** each having an individual thin encapsulation **45** (**FIGS. 6a, 6b**), **52** (**FIG. 11**) and **62** (**FIGS. 7a, 7b**), respectively. The encapsulation preferably comprises a moisture-proof material or coating such as silicone, paralene or acrylic. The thin encapsulation may be made soft, such as soft silicone, or rigid, such as hard acrylic. Any exposed part of connector **53** extending from battery assembly **50** must be moisture-proofed in order to protect the hearing device from the damaging affects of moisture produced within or outside the ear canal.

Sub P3
The connector 53 and battery 51 are encapsulated by a thin disposable enclosure 52 according to the disclosure of the '764 application. The battery assembly 50 minimally occludes the ear canal and is preferably positioned substantially at or beyond the bony-cartilaginous junction 19 (FIG. 1; see, also, J of FIG. 17).

5 In order to protect the microphone and receiver of the hearing device 30 from the damaging effects of moisture and debris, microphone debris guard 42 (FIG. 5) and receiver debris guard 67 are placed on microphone and receiver ports 46 and 63, respectively. The microphone guard 42 in the embodiments of FIGS. 4 and 5 is in the form of a replaceable cap with a cap body 48 (FIG. 5) fitted over the microphone port 46 (in the direction of arrow 31) and guard member 47 made of a thin membrane or screen material that is substantially transparent to sound. Similarly, receiver guard 67 (FIG. 5) may also be in the form of a replaceable cap with cap body 65 fitted over the receiver in the direction of arrow 32 with guard member 65 positioned over receiver sound port 63. The effect of the microphone and receiver guards 42 and 67, respectively, on the acoustic response of the hearing device is detailed below in the section titled Experiment-C.

Sub P4
10
15

When the hearing device 30 is fully inserted in its normal position in the ear canal 10, the microphone assembly 40 is positioned at the cartilaginous region 11 with a substantial air-space 49 all around the microphone assembly (FIGS. 6a, 6b), between the enclosure 45 of the microphone assembly and the canal skin 16 (walls). The microphone assembly 40 is positioned substantially clear from hair 12 and physiologic debris 4 produced in the cartilaginous region 11.

20

The alternate ear canal 10' of FIG. 6b is depicted as being relatively narrow, and although a substantial air-space 49 is also present, the microphone assembly 40 makes minimal contact with the wall of the canal or with physiologic debris 4 therein at the contact area 5. However, connector 53, which is flexibly connected to battery assembly 50 in the preferred embodiment, allows microphone assembly 40 freedom to move along the cross-section of the ear canal in response to pressure from physiologic debris 4 production or canal deformations associated with jaw movements.

As shown in FIGS. 7a and 7b, the receiver assembly 60 is positioned in ear canal 10 at bony area 13, with sealing retainer 70 in direct contact with canal skin 14 (walls), thus occluding the bony area of the canal. A vent 61 (FIGS. 5 and 7a) is provided for pressure equalization during insertion and removal or during changes in atmospheric pressure. The vent may alternatively be provided across the sealing retainer 70 (FIG. 7b). The vent 61 is also provided to minimize occlusion effects described above.

The microphone assembly 40 in the preferred embodiment of FIGS 4-6, comprises a microphone 43, a control element 41 (i.e., volume trimmer as shown in FIG. 5) and switch assembly 44. The switch assembly 44 comprises a latchable read-switch assembly (RS in FIG. 8), which is remotely activated by a remote magnet (e.g., 120 in FIG. 13) according to the disclosure in the '533 application. The microphone 43 comprises a microphone transducer with an integrated signal processing amplifier (for example, series FI-33XX manufactured by Knowles Electronics of Itasca, IL). This integration reduces the size of the microphone assembly, which further reduces occlusion effects within the ear canal at the

cartilaginous region. Alternatively, the signal processing amplifier may be a separate component, as shown at 28 in the embodiment of FIG. 12.

A schematic diagram of an electroacoustic circuit of the embodiment in FIGS. 4-7 is shown in FIG. 8. The microphone M, comprising a microphone transducer and signal processing amplifier integrated therein, picks up acoustic signals S_M entering the ear canal and produces amplified electrical signal at terminal OUT of microphone M. The electrical signal is then delivered to input (IN) terminal of the receiver R via coupling capacitors C1 and C2. The receiver R then produces amplified acoustic signal S_R for delivery to the tympanic membrane 18 (FIG. 4). Volume trimmer R_G , connecting the output (OUT) and feedback (FB) terminals of the microphone M, is adjusted to set the gain (volume) of the electroacoustic circuit. Jumper J1 (also shown in FIG. 5) may be removed (by cutting for example) to reduce the coupling capacitance, thus altering the frequency response of the hearing device as known to those skilled in the art of electronics. Other jumpers (not shown) may also be incorporated in order to increase the range of adjustable parameters of the hearing device. A capacitor C_R is employed to stabilize the supply voltage (V+) across the supply terminals (+ and -) of the receiver R.

The acoustic response of a device fabricated according to the embodiment of FIGS. 4-7 and the electroacoustic circuit of FIG. 8 was measured and plotted in FIG. 9 with and without moisture-proof guards as detailed below in the section titled Experiment-C.

The connector 53, in the preferred embodiment shown in more detail in FIG. 10, comprises a flexible film 54 with circuit wires 55, 56, 57 and 58, which electrically

interconnect the microphone 43, receiver 64, battery 51, volume trimmer 41, and other components (which are not shown, for the sake of clarity), such as switch assembly 44 (shown in FIG. 5) and capacitors. The microphone 43 (shown unassembled) is soldered to the connector 53 via solder terminals 81 on the lateral section 83 of the flexible film 54 and solder terminals 81' on the microphone 43. Similarly the receiver 64 is soldered to the connector 53 via solder terminals 82 on the medial section 85 of the flexible film 54 and solder terminals 82' on the receiver 64. Conductive pads 91 and 92 on the connector provide power connectivity from the positive 94 and negative 97 (FIG. 11) terminals, respectively, of the battery 51. Volume trimmer 41 is also connected to solder terminals 81 via trimmer solder terminals 41'.

The lateral and medial sections 83 and 85 respectively of film 54 are flexibly bendable with respect to the main section 87, thus allowing the connected microphone assembly 40 and receiver assembly 60 to articulate within the ear canal during insertion and removal of the hearing device. A crossing section 88 of the connector 53 also bends in the direction of arrow 93 (into the paper) in order to connect conductive pad 92 to the negative terminal 97 (FIG. 11) of the battery. The flexible film 54 is provided with relief notches 84, 86 and 89 which increase the flexibility of the sections 83, 85 and 88, respectively. The battery 51, main section 87, and crossing section 88, are encapsulated by thin disposable battery encapsulation 52 (FIG. 11) for securing the connector 53 and the associated conductive pads 91 and 92 to the battery. The main section 87 includes a vent hole 95 for allowing air circulation to battery hole 96, typically available in air-zinc hearing aid batteries. Similarly, the battery encapsulation 52 must allow for the necessary aeration of the battery enclosed therein.

FIG. 11 shows a cross sectional view of the battery assembly **50** in the ear canal **10** showing main section **87** of connector **53**, battery **51** and battery encapsulation **52**. The crossing section **88**, extending from main section **87** is also shown crossing to the negative terminal **97** of the button cell battery **51**. Circuit wires **55**, **56** and **57** are also shown. The battery encapsulation **52** is thin and substantially conforms to the shape of the battery, thus adding negligible dimensions to the enclosed battery. The battery enclosure should be less than 0.3 mm in thickness in order for the battery assembly to minimally occlude the ear canal and to fit comfortably in the vicinity of the bony-cartilaginous area for most individuals.

In another embodiment, shown in **FIG. 12**, the hearing device **100** has a microphone assembly **40**, which extends substantially laterally in the cartilaginous area **11** as shown. The sealing retainer **70**, although remaining substantially in the bony region **13**, is concentrically positioned over both the receiver assembly **60** and the battery assembly **50**. The receiver assembly **60** protrudes from the sealing retainer medially towards the tympanic membrane **18**. The hearing device **100** is also shown as being programmable with a programming receptacle **101** for receiving programming signals from a programming connector **102**. The programming connector comprises programming pins **103** which are temporarily inserted into the programming receptacle **101** during the programming of the hearing device **100**. The capability to be programmable allows hearing device **100** to be electronically adjusted via an external programming device **105 (P)** and its associated programming cable **106**. Other means for remotely programming or adjusting a hearing device are well known in the field of hearing aids and include the use of sound, ultrasound, radio-frequency (RF), infra-

red (IR) and electromagnetic (EM) signals.

FIG. 12 also shows a probe tube system **110** for the measurement of sound pressure level (SPL) produced by the hearing device **100** in the ear canal. The probe tube system comprises a probe tube **111**, a microphone **112** and amplifier (A) **113**. Electrical cable **116** connects the microphone **112** to the amplifier **113**. The probe tube **111** is inserted in the ear canal with its tip **115** past the receiver assembly **60** near the tympanic membrane **18**. Probe tube measurements in the ear canal are employed during the fitting process for the *in-situ* (while in the ear canal) electroacoustic adjustment and verification of the fitted hearing device.

Removal handle **107** may be provided for the removal of the hearing device **100**, particularly during an emergency situation, such as infection of the ear canal or irritation therein.

In a preferred embodiment of a remote control, shown in **FIG. 13**, the hearing device **30** comprises a latchable reed-switch assembly **44** (RS) for remotely powering the hearing device ON/OFF via an external control magnet **120** which is positioned by the wearer (user) at the vicinity of the concha **2**. The control magnet **120** in the preferred embodiment has two opposing polarities; a north (N) pole **121** and south (S) pole **122**, across the length of the control magnet **120** as shown. The flux lines **123** emanating from the north pole towards the south pole affect the lateral (nearer) lead **44'** of latchable reed-switch assembly **44**. Flux lines **123** either latch on or off the reed-switch assembly **44** according to the polarity of the control magnet **120** nearest to lead **44'**. The read-switch assembly **44** comprises a latching magnet (not shown) as disclosed in greater detail in the aforementioned '533 application, and allows hearing

device 30 to be turned off to conserve battery power during sleep and other non-use periods while the device remains in the ear canal for long-term use.

The encapsulations 45 and 62 of the microphone receiver assemblies 40 and 60, respectively, are each made of thin protective material that substantially conforms to the shape of the components encapsulated therein. The thickness of each encapsulation is preferably less than 0.3 mm in order to minimize occlusion of the microphone assembly 40 (see FIGS. 6a and 6b) in the ear canal and to maximize the relative dimension of the conforming sealing retainer 70 in the bony region 13 (see FIGS. 7a and 7b). Since the semi-permanent hearing device of the invention is handled relatively infrequently, the thickness of the encapsulation can be safely made substantially thinner than conventional enclosures of CIC devices which are typically in the range of 0.5 - 0.7 mm.

In another embodiment of the moisture-proof debris guard, shown in FIGS. 14a and 14b for a receiver assembly 60, the debris guard 67 is made in the form of an adhesive pad. The receiver debris guard is composed of an acoustically-transparent material 65 with an adhesive layer 69 on its lateral surface for attachment to the medial surface 63' of receiver assembly 60. The receiver assembly's medial surface 63' includes the receiver sound port 63 which emits receiver sound S_R that passes through the debris guard 67 as illustrated by the arrow. The adhesive layer 69 is partially relieved from adhesive material in the adhesive-free area 65' corresponding to or mating with receiver sound port 63. The adhesive-free area 65' is necessary since adhesives are generally not acoustically transparent, and thus will adversely alter the frequency response of the receiver 64 if applied directly over the sound port 63. The

adhesive pad configuration of the debris guard is equally applicable for both the microphone and receiver sound ports, as shown at **42** and **67**, respectively, in **FIGS. 12-15**. The adhesive pad is preferably replaceable and disposable.

The present invention, shown with button cell batteries in the above
5 embodiments, is equally suited to accommodate other battery shapes and configurations as they are likely to be available in future hearing aid applications. The thin enclosure of the battery assembly of the present invention, regardless of the type of battery used, conforms substantially to the shape of the enclosed battery with encapsulation thickness not to exceed 0.3 mm for the preferred embodiments of the invention.

For example, in another embodiment of the present invention, shown in **FIG.**
15, a cylindrical battery **51** is employed with a hearing device **130** substantially positioned in the bony region **13** of the ear canal **10**. The microphone end **132** of the core assembly **35** extends laterally and non-occlusively in the cartilaginous region **11**. The receiver end **133** is coaxially positioned within sealing retainer **70**, which acoustically seals and conforms in the bony region **13**. A thin encapsulation **131**, not exceeding 0.3 mm, protects the entire core assembly **35**, which comprises the microphone **43**, battery **51** and receiver **64** therein.

The sealing retainer **70**, shown in greater detail in **FIG. 16**, comprises a soft compressible and conforming material such as polyurethane foam or like material (a polymer) or silicone or like material. The sealing retainer **70** must provide significant acoustic
20 attenuation in order to seal and prevent feedback. In a preferred embodiment of the sealing retainer fabricated and tested within ear canals of individuals, a polyurethane foam sealing

retainer was molded from a mixture of 1-part aqueous solution (Polymer component Type 1A, manufactured by Hamshire Chemicals, Lexington, MA) and 2-part prepolymer (HYPOL™ 2002 also manufactured by Hamshire Chemicals). The mixture was poured into a silicone mold (REDU-IT™ manufactured by American Dental Supply Co. of Easton, PA) and allowed to
5 heat cure at approximately 195° F for about 15 minutes prior to removing from the silicone mold at room temperature.

The molded sealing retainer 70 did not include any rigid core material therein in order to maximize the fit and comfort within the bony region of the ear canal. The sealing retainer 70 was made oval with long diameter D_L approximately 1.6 times that of the short diameter D_s . The inferior (lower) portion 74 is relatively pointed to match the shape of typical ear canals in the bony region. The sealing retainer 70 is substantially hollow with air-space 72 between the body 73 of the sealing retainer and the receiver assembly 60 when inserted therein. The medial opening 71 of the sealing retainer is stretchable and is made smaller than the diameter of the receiver assembly 60 in order to provide a tight fit for sealing and securing the receiver assembly and the associated hearing device within the ear canal. Vertical and horizontal cavities 75 and 76, respectively, in the shape of a cross, extend medially from the lateral end of the sealing retainer 70. These cavities, in conjunction with the internal air-space 72, increase the compressibility and conformity of the sealing retainer so that it can be worn more comfortably in the bony region 13 which is known for being extremely sensitive to
20 pressure. Furthermore, the cavities 75 and 76 allow for partial enclosure of the battery assembly (dotted circle) 50 therein as shown in FIG. 16a.

The sealing retainer 70, made of polyurethane foam material for example as described above, is compressible and subsequently expandable with time, thus allowing for a temporary compression state prior to and during insertion into the ear canal and a subsequent expansion to conform to the ear canal and seal therein.

5 In a preferred embodiment according to the invention, the sealing retainer 70 was fabricated in an assortment of four sizes (small, medium, large and extra-large) to accommodate the broadest range of ear canals among the population studied. The dimensions of such fabricated assortment are tabulated in Table 1 below. The dimensions were partially derived from measurements of actual ear canal dimensions obtained from cadaver impressions as explained below in the section titled Experiment-A. The sealing retainer may be produced in an assortment of other sizes and shapes as needed to accommodate an even wider diversity of ear canals when studied.

Table 1

Size	Short Diameter (D ₁) in mm	Large Diameter (D ₂) in mm
Small	4.5	7.25
Medium	5.75	9.35
Large	7.3	12
Ex-Large	9.0	15

20 The sealing retainer is preferably disposable and must be biocompatible and hypoallergenic for a safe prolonged wear in the ear canal. The sealing retainer may incorporate a vent 6 as shown in FIG. 7b. This vent may created by inserting or molding a narrow-diameter silicone tube therein, for example.

Certain individuals may have difficulty wearing the sealing retainer due to the sensitivity of their ear canal, medical condition, or other concerns. Therefore, the sealing retainer may be separately inserted, without the core assembly, for a period of time sufficient to assess comfort and appropriateness of wear prior to inserting the entire hearing device semi-permanently. This may represent a "trial wear" for an individual who may be reluctant to wear or purchase the device for whatever reason.

The semi-permanent hearing device of the present invention comprises a disposable battery, disposable battery enclosure, or alternatively a disposable battery assembly with combined battery and enclosure. However, as energy efficiency improvements in battery, circuit and transducer technologies continue to improve, the preferred embodiment may be that of a disposable core assembly with assorted sealing retainers as described above.

Experiment A.

In a study performed by the applicants herein, the cross-sectional dimensions of ear canals were measured from 10 canal impressions obtained from adult cadaver ears. The long (vertical) and short (horizontal) diameters, D_L and D_S respectively, of cross sections at the center of three regions in the ear canal (see FIGS 2 and 17) were measured and tabulated. These regions represent the cartilaginous (C), the bony-cartilaginous junction (J), and the bony (B) regions. The diameters were measured across the widest points of each cadaver impression at each region. All measurements were taken by a digital caliper (model CD-6"CS manufactured by Mitutoyo). The impression material used was low viscosity Hydrophilic Vinyl

Polysiloxane (manufactured by Densply/Caulk) using a dispensing system (model Quixx manufactured by Caulk). Measurements are set forth in Table 2, below.

Table 2

Sample #	C-Region Diameters in mm		J-Region Diameters in mm		B-Region Diameters in mm	
	Short (D _s)	Long (D _L)	Short (D _s)	Long (D _L)	Short (D _s)	Long (D _L)
1-R	7.8	10.3	8.1	10.7	8.0	10.5
1-L	7.8	11.9	8.3	12.2	8.1	11.2
2-R	3.8	8.9	4.0	8.9	4.2	8.9
2-L	5.3	8.1	4.4	8.8	4.3	8.6
3-R	5.5	6.3	4.7	6.7	5.0	7.7
3-L	4.9	6.5	4.9	6.5	4.9	7.3
4-R	6.9	9.2	6.5	9.6	6.7	10.4
5-R	6.9	9.2	7.2	8.4	7.5	9.5
5-L	6.8	8.2	7.6	9.4	7.5	8.7
7-L	6.3	7.0	5.1	6.7	4.9	6.7
Average	6.2	8.6	6.1	8.8	6.1	9.0

Results and Conclusion

The diameter dimensions of the ear canal vary significantly among adult individuals. In general, variations occur more so across the short (horizontal) diameters. Furthermore, the ear canal is slightly narrower (long/short ratio) in the bony region than in the other two regions. Although not apparent from the above measurements, the cartilaginous region is expandable which facilitates insertion of wider objects through it towards the deeper region, if necessary.

Experiment B

A test of insertion fit of the semi-permanent canal device was performed using the battery assembly of the invention. The battery assembly was selected because it represents the largest of all assemblies in the hearing device according to the present invention.

5 Using the 10 cadaver impressions described above in Experiment-A, 10 actual-size ear canal models were fabricated by dip-forming clear acrylic material (Audacryl-acrylic manufactured by Esschem). Two battery assemblies according to the embodiment of **FIGS. 10-11** were fabricated and inserted in each of the 10 ear canal models up to the bony-cartilaginous junction area. The first assembly comprised a size-10A battery and the second comprised size-312 battery (each is a standard button cell hearing aid battery; see **FIG. 2**). Each battery assembly included a thin flexible connector and was encapsulated with silicone conformal coating (model MED 10-6605 manufactured by NuSil). The thickness of the coating measured approximately 0.05 mm, thus adding negligible dimensions to the battery assembly and flexible connector thereof. The diameter (D) and height (H) of each assembly was measured across the widest points as tabulated in Table 3, below.

FIG. 2 is a cross-sectional view of the ear canal at the bony-cartilaginous junction for (a) the smallest canal, (b) an average size canal and (c) the largest canal. The relative dimensions of standard 10A and 312 batteries are also shown.

20 The thickness of several shells of conventional hearing devices were also measured for comparison analysis (measuring between 0.5 mm and 0.7 mm). For a conventional hearing device enclosing size-10A battery, the added dimensions of (1) the shell

(0.5 mm or more, adding a minimum of 1 mm to the dimensions) and (2) other enclosed components, prohibit insertion of the device at the bony-cartilaginous junction (**J**) area for at least 5 of the above ear canals (2-R, 2-L, 3-R, 3-L and 7-L). This is further exacerbated by the fact that ear canals are often tortuously contoured, thus making it painful if not impossible to insert the conventional CIC device too deeply in seeking to gain access to the bony region of the ear canal. For conventional CIC devices with size-312 battery (larger than 10-A), deep fitting is only likely for very large ear canals, such as 1-R and 1-L.

Table 3

Battery Assembly	Height (H) in mm	Diameter (D) in mm
10A Bat.	4.4 (H)	6.5 (D)
312 Bat.	4.5 (H)	8.0 (D)

Results and Conclusion

The first battery assembly (size-10A) was successfully inserted up to the bony-cartilaginous junction (**J**) region in 9 of the 10 ear canal models, excepting 2-R which has dimensions of 4.0 x 8.9 mm (**D_S** x **D_L**) as shown in **FIG. 2**.

The second battery assembly (size-312) was successfully inserted up to the bony-cartilaginous junction in 5 of the 10 ear canal models. This is particularly significant, since size-312 batteries are virtually excluded from conventional CIC devices due to their excessive size in conjunction with conventional CIC designs.

The results confirm that the present invention is more space-efficient and would allow the battery assembly to fit in the bony-cartilaginous junction area and beyond for most adult individuals with size-10A batteries and a significant percentage of adult individuals with size-312 batteries.

5 Experiment C

A prototype of the semi-permanent hearing device according to the embodiment of FIGS. 4-10 was fabricated and positioned by an otolaryngologist (ear-nose-throat physician) in the left ear canal of a 55 year old male subject who suffered a moderate level of high frequency hearing loss.

0065377-0990
The circuit of FIG. 8 was implemented with a miniature microphone/amplifier (model FI-3342 manufactured by Knowles Electronics of Itasca, IL), class-D receiver (model FS3379 also manufactured by Knowles Electronics), and miniature 250K ohm volume trimmer R_G (model PJ-62 manufactured by Microtronics A/S of Denmark). Miniature capacitors C1, C2 and C_R with values of 2.2 nF, .01 uF and 2.2 uF, respectively were employed. A reed
15 switch assembly (RS) employing a miniature reed-switch (model HSR-003DT, manufactured by Hermetic Switch, Inc. of Chickasha, Oklahoma) and a miniature Neodymium Iron Boron (NdFeB) magnet for latching the reed-switch.

Two layers of thin Kapton tape (#042198 GUA distributed by Economic Packaging Corp. of Milpitas, California) were employed to fabricate a thin flexible connector
20 which embedded circuit wires made of 44 AWG Litz wire.

The microphone assembly, comprising microphone amplifier **M**, reed-switch assembly **RS**, volume trimmer **R_G**, and lateral section **83** of flexible connector **53** were glued together using cyanoacrylate (#20269, manufactured by Loctite Corp. of Rocky Hill, CT). The microphone assembly was then encapsulated by thin moisture proofing silicone material (E41
5 manufactured by Wacker, Werk Burghausen of Germany). The receiver assembly, comprising receiver and **C_R** capacitor was similarly encapsulated by silicone material and was flexibly connected to the Kapton tape connector.

The moisture-proof debris guard for the microphone and receiver ports employed Gore-Tex™ material (# VE00105 manufactured by W.L. Gore & Associates of Elkton, MD) for guard member and polypropylene plastic (#100-8932 distributed by Henry Schein/ZAHN of Esschem of Port Washington, NY) for the body of the guard cap. The guard member material was approximately 0.2 mm in thickness.

A large-sized sealing retainer was fabricated using the above mentioned polymer foam material and fabrication process.

The device, excluding the retainer seal, weighed 0.73 grams, including the 10A battery which weighed 0.29 grams alone.

The subject was provided with a control magnet, in the shape of a bar, for remotely switching the device on or off as desired.

The acoustic response of the prototype device was measured in a standard CIC coupler (Manufactured by Frye Electronics) and plotted in **FIG. 9**. The response was measured without debris guard (thick solid line labeled No Moisture Guard), with receiver
20

guard (solid line labeled Moisture Guard on Receiver Only), and with debris guards on both receiver and microphone (dotted line labeled Moisture Guard on Receiver and Microphone).

Results and Conclusion

5 There was a slight sound degradation (approximately 4 decibels (dB)) at frequencies of 3000 and above compared to the No Moisture Guard condition. However, this represents a minimal acoustic impact which can be easily compensated for electronically or by the employment of thinner guard material.

005277-09066760
15 The prototype device, including receiver and microphone debris guards according to the embodiment of FIG. 5, and the sealing retainer, was worn deeply and completely inconspicuously in the ear canal of the 55 year old subject. The tip of the receiver was approximately 2-3 mm from the tympanic membrane. The volume trimmer was adjusted *in-situ* by a miniature screwdriver until the preferred volume level was reached for the subject who reported good sound fidelity and comfort of wear. The device was worn comfortably during sleep. The subject was also able to shower while the device was in the ear canal without adverse affects on the perceived quality of sound.

20 It should also be noted that the moisture-proofing provided by the debris guards and enclosures according to the invention can even afford the wearer the opportunity to engage in normal swimming without fear of damage to or loss of fidelity of the hearing device. It would not be recommended that the wearer engage in diving or prolonged underwater swimming, however.

It is also worth emphasis that the sealing retainer itself provides significant advantages for use with a semi-permanent hearing device adapted to be inserted entirely within the ear canal of a wearer past the aperture. The sealing retainer is configured for concentric positioning over a medial part of a core assembly of the hearing device so that the core assembly extends laterally within and makes minimal or no contact with the walls of the cartilaginous region of the ear canal. The core assembly is suspended within and snugly supported at the medial part by the sealing retainer, and is arranged and adapted to protrude medially beyond the sealing retainer in a preferred embodiment. The sealing retainer is further configured for seating securely within and occluding the bony region of the ear canal when the semi-permanent hearing device is fully inserted within the ear canal of the wearer. The sealing retainer is sufficiently soft and yielding to conform itself to the shape of the ear canal in the bony region.

Consequently, the sealing retainer provides acoustic sealing of the bony region to prevent feedback, and the lateral extension of the core assembly avoids substantial interference with hair and production of cerumen and debris in the cartilaginous region.

According to another aspect of the invention, in a method of testing a hearing-impaired individual's tolerance to long-term wearing of a semi-permanent hearing device inserted entirely within the ear canal past the aperture thereof, the testing is performed without requiring the individual to actually wear the entire hearing device. The method includes a first step of inserting the sealing retainer into the ear canal, with the air cavity of the retainer unoccupied by the core assembly, until the retainer is seated securely against the walls in the

bony region. The sealing retainer is removed from the ear canal after having been worn by the individual for a period of sufficient length to determine the long-term tolerance. The individual is interviewed to assess his or her view of the level of comfort and sensitivity to the presence of the device in the ear canal. The ear canal is also examined after removal of the sealing
5 retainer.

It is highly desirable to maintain an inventory of assorted sizes and shapes of the sealing retainer for selection of an appropriate fit for the ear canal of the individual.

Although a presently contemplated best mode of practicing the invention has been described herein, it will be recognized by those skilled in the art to which the invention pertains from a consideration of the foregoing description of presently preferred and alternate embodiments and methods of fabrication and use thereof, that variations and modifications of this exemplary embodiments and methods may be made without departing from the true spirit and scope of the invention. Thus, the above-described embodiments of the invention should not be viewed as exhaustive or as limiting the invention to the precise configurations or techniques disclosed. Rather, it is intended that the invention shall be limited only by the
10
15
20
25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995
1000
1005
1010
1015
1020
1025
1030
1035
1040
1045
1050
1055
1060
1065
1070
1075
1080
1085
1090
1095
1100
1105
1110
1115
1120
1125
1130
1135
1140
1145
1150
1155
1160
1165
1170
1175
1180
1185
1190
1195
1200
1205
1210
1215
1220
1225
1230
1235
1240
1245
1250
1255
1260
1265
1270
1275
1280
1285
1290
1295
1300
1305
1310
1315
1320
1325
1330
1335
1340
1345
1350
1355
1360
1365
1370
1375
1380
1385
1390
1395
1400
1405
1410
1415
1420
1425
1430
1435
1440
1445
1450
1455
1460
1465
1470
1475
1480
1485
1490
1495
1500
1505
1510
1515
1520
1525
1530
1535
1540
1545
1550
1555
1560
1565
1570
1575
1580
1585
1590
1595
1600
1605
1610
1615
1620
1625
1630
1635
1640
1645
1650
1655
1660
1665
1670
1675
1680
1685
1690
1695
1700
1705
1710
1715
1720
1725
1730
1735
1740
1745
1750
1755
1760
1765
1770
1775
1780
1785
1790
1795
1800
1805
1810
1815
1820
1825
1830
1835
1840
1845
1850
1855
1860
1865
1870
1875
1880
1885
1890
1895
1900
1905
1910
1915
1920
1925
1930
1935
1940
1945
1950
1955
1960
1965
1970
1975
1980
1985
1990
1995
2000
2005
2010
2015
2020
2025
2030
2035
2040
2045
2050
2055
2060
2065
2070
2075
2080
2085
2090
2095
2100
2105
2110
2115
2120
2125
2130
2135
2140
2145
2150
2155
2160
2165
2170
2175
2180
2185
2190
2195
2200
2205
2210
2215
2220
2225
2230
2235
2240
2245
2250
2255
2260
2265
2270
2275
2280
2285
2290
2295
2300
2305
2310
2315
2320
2325
2330
2335
2340
2345
2350
2355
2360
2365
2370
2375
2380
2385
2390
2395
2400
2405
2410
2415
2420
2425
2430
2435
2440
2445
2450
2455
2460
2465
2470
2475
2480
2485
2490
2495
2500
2505
2510
2515
2520
2525
2530
2535
2540
2545
2550
2555
2560
2565
2570
2575
2580
2585
2590
2595
2600
2605
2610
2615
2620
2625
2630
2635
2640
2645
2650
2655
2660
2665
2670
2675
2680
2685
2690
2695
2700
2705
2710
2715
2720
2725
2730
2735
2740
2745
2750
2755
2760
2765
2770
2775
2780
2785
2790
2795
2800
2805
2810
2815
2820
2825
2830
2835
2840
2845
2850
2855
2860
2865
2870
2875
2880
2885
2890
2895
2900
2905
2910
2915
2920
2925
2930
2935
2940
2945
2950
2955
2960
2965
2970
2975
2980
2985
2990
2995
3000
3005
3010
3015
3020
3025
3030
3035
3040
3045
3050
3055
3060
3065
3070
3075
3080
3085
3090
3095
3100
3105
3110
3115
3120
3125
3130
3135
3140
3145
3150
3155
3160
3165
3170
3175
3180
3185
3190
3195
3200
3205
3210
3215
3220
3225
3230
3235
3240
3245
3250
3255
3260
3265
3270
3275
3280
3285
3290
3295
3300
3305
3310
3315
3320
3325
3330
3335
3340
3345
3350
3355
3360
3365
3370
3375
3380
3385
3390
3395
3400
3405
3410
3415
3420
3425
3430
3435
3440
3445
3450
3455
3460
3465
3470
3475
3480
3485
3490
3495
3500
3505
3510
3515
3520
3525
3530
3535
3540
3545
3550
3555
3560
3565
3570
3575
3580
3585
3590
3595
3600
3605
3610
3615
3620
3625
3630
3635
3640
3645
3650
3655
3660
3665
3670
3675
3680
3685
3690
3695
3700
3705
3710
3715
3720
3725
3730
3735
3740
3745
3750
3755
3760
3765
3770
3775
3780
3785
3790
3795
3800
3805
3810
3815
3820
3825
3830
3835
3840
3845
3850
3855
3860
3865
3870
3875
3880
3885
3890
3895
3900
3905
3910
3915
3920
3925
3930
3935
3940
3945
3950
3955
3960
3965
3970
3975
3980
3985
3990
3995
4000
4005
4010
4015
4020
4025
4030
4035
4040
4045
4050
4055
4060
4065
4070
4075
4080
4085
4090
4095
4100
4105
4110
4115
4120
4125
4130
4135
4140
4145
4150
4155
4160
4165
4170
4175
4180
4185
4190
4195
4200
4205
4210
4215
4220
4225
4230
4235
4240
4245
4250
4255
4260
4265
4270
4275
4280
4285
4290
4295
4300
4305
4310
4315
4320
4325
4330
4335
4340
4345
4350
4355
4360
4365
4370
4375
4380
4385
4390
4395
4400
4405
4410
4415
4420
4425
4430
4435
4440
4445
4450
4455
4460
4465
4470
4475
4480
4485
4490
4495
4500
4505
4510
4515
4520
4525
4530
4535
4540
4545
4550
4555
4560
4565
4570
4575
4580
4585
4590
4595
4600
4605
4610
4615
4620
4625
4630
4635
4640
4645
4650
4655
4660
4665
4670
4675
4680
4685
4690
4695
4700
4705
4710
4715
4720
4725
4730
4735
4740
4745
4750
4755
4760
4765
4770
4775
4780
4785
4790
4795
4800
4805
4810
4815
4820
4825
4830
4835
4840
4845
4850
4855
4860
4865
4870
4875
4880
4885
4890
4895
4900
4905
4910
4915
4920
4925
4930
4935
4940
4945
4950
4955
4960
4965
4970
4975
4980
4985
4990
4995
5000
5005
5010
5015
5020
5025
5030
5035
5040
5045
5050
5055
5060
5065
5070
5075
5080
5085
5090
5095
5100
5105
5110
5115
5120
5125
5130
5135
5140
5145
5150
5155
5160
5165
5170
5175
5180
5185
5190
5195
5200
5205
5210
5215
5220
5225
5230
5235
5240
5245
5250
5255
5260
5265
5270
5275
5280
5285
5290
5295
5300
5305
5310
5315
5320
5325
5330
5335
5340
5345
5350
5355
5360
5365
5370
5375
5380
5385
5390
5395
5400
5405
5410
5415
5420
5425
5430
5435
5440
5445
5450
5455
5460
5465
5470
5475
5480
5485
5490
5495
5500
5505
5510
5515
5520
5525
5530
5535
5540
5545
5550
5555
5560
5565
5570
5575
5580
5585
5590
5595
5600
5605
5610
5615
5620
5625
5630
5635
5640
5645
5650
5655
5660
5665
5670
5675
5680
5685
5690
5695
5700
5705
5710
5715
5720
5725
5730
5735
5740
5745
5750
5755
5760
5765
5770
5775
5780
5785
5790
5795
5800
5805
5810
5815
5820
5825
5830
5835
5840
5845
5850
5855
5860
5865
5870
5875
5880
5885
5890
5895
5900
5905
5910
5915
5920
5925
5930
5935
5940
5945
5950
5955
5960
5965
5970
5975
5980
5985
5990
5995
6000
6005
6010
6015
6020
6025
6030
6035
6040
6045
6050
6055
6060
6065
6070
6075
6080
6085
6090
6095
6100
6105
6110
6115
6120
6125
6130
6135
6140
6145
6150
6155
6160
6165
6170
6175
6180
6185
6190
6195
6200
6205
6210
6215
6220
6225
6230
6235
6240
6245
6250
6255
6260
6265
6270
6275
6280
6285
6290
6295
6300
6305
6310
6315
6320
6325
6330
6335
6340
6345
6350
6355
6360
6365
6370
6375
6380
6385
6390
6395
6400
6405
6410
6415
6420
6425
6430
6435
6440
6445
6450
6455
6460
6465
6470
6475
6480
6485
6490
6495
6500
6505
6510
6515
6520
6525
6530
6535
6540
6545
6550
6555
6560
6565
6570
6575
6580
6585
6590
6595
6600
6605
6610
6615
6620
6625
6630
6635
6640
6645
6650
6655
6660
6665
6670
6675
6680
6685
6690
6695
6700
6705
6710
6715
6720
6725
6730
6735
6740
6745
6750
6755
6760
6765
6770
6775
6780
6785
6790
6795
6800
6805
6810
6815
6820
6825
6830
6835
6840
6845
6850
6855
6860
6865
6870
6875
6880
6885
6890
6895
6900
6905
6910
6915
6920
6925
6930
6935
6940
6945
6950
6955
6960
6965
6970
6975
6980
6985
6990
6995
7000
7005
7010
7015
7020
7025
7030
7035
7040
7045
7050
7055
7060
7065
7070
7075
7080
7085
7090
7095
7100
7105
7110
7115
7120
7125
7130
7135
7140
7145
7150
7155
7160
7165
7170
7175
7180
7185
7190
7195
7200
7205
7210
7215
7220
7225
7230
7235
7240
7245
7250
7255
7260
7265
7270
7275
7280
7285
7290
7295
7300
7305
7310
7315
7320
7325
7330
7335
7340
7345
7350
7355
7360
7365
7370
7375
7380
7385
7390
7395
7400
7405
7410
7415
7420
7425
7430
7435
7440
7445
7450
7455
7460
7465
7470
7475
7480
7485
7490
7495
7500
7505
7510
7515
7520
7525
7530
7535
7540
7545
7550
7555
7560
7565
7570
7575
7580
7585
7590
7595
7600
7605
7610
7615
7620
7625
7630
7635
7640
7645
7650
7655
7660
7665
7670
7675
7680
7685
7690
7695
7700
7705
7710
7715
7720
7725
7730
7735
7740
7745
7750
7755
7760
7765
7770
7775
7780
7785
7790
7795
7800
7805
7810
7815
7820
7825
7830
7835
7840
7845
7850
7855
7860
7865
7870
7875
7880
7885
7890
7895
7900
7905
7910
7915
7920
7925
7930
7935
7940
7945
7950
7955
7960
7965
7970
7975
7980
7985
7990
7995
8000
8005
8010
8015
8020
8025
8030
8035
8040
8045
8050
8055
8060
8065
8070
8075
8080
8085
8090
8095
8100
8105
8110
8115
8120
8125
8130
8135
8140
8145
8150
8155
8160
8165
8170
8175
8180
8185
8190
8195
8200
8205
8210
8215
8220
8225
8230
8235
8240
8245
8250
8255
8260
8265
8270
8275
8280
8285
8290
8295
8300
8305
8310
8315
8320
8325
8330
8335
8340
8345
8350
8355
8360
8365
8370
8375
8380
8385
8390
8395
8400
8405
8410
8415
8420
8425
8430
8435
8440
8445
8450
8455
8460
8465
8470
8475
8480
8485
8490
8495
8500
8505
8510
8515
8520
8525
8530
8535
8540
8545
8550
8555
8560
8565
8570
8575
8580
8585
8590
8595
8600
8605
8610
8615
8620
8625
8630
8635
8640
8645
8650
8655
8660
8665
8670
8675
8680
8685
8690
8695
8700
8705
8710
8715
8720
8725
8730
8735
8740
8745
8750
8755
8760
8765
8770
8775
8780
8785
8790
8795
8800
8805
8810
8815
8820
8825
8830
8835
8840
8845
8850
8855
8860
8865
8870
8875
8880
8885
8890
8895
8900
8905
8910
8915
8920
8925
8930
8935
8940
8945
8950
8955
8960
8965
8970
8975
8980
8985
8990
8995
9000
9005
9010
9015
9020
9025
9030
9035
9040
9045
9050
9055
9060
9065
9070
9075
9080
9085
9090
9095
9100
9105
9110
9115
9120
9125
9130
9135
9140
9145
9150
9155
9160
9165
9170
9175
9180
9185
9190
9195
9200
9205
9210
9215
9220
9225
9230
9235
9240
9245
9250
9255
9260
9265
9270
9275
9280
9285
9290
9295
9300
9305
9310
9315
9320
9325
9330
9335
9340
9345
9350
9355
9360
9365
9370
9375
9380
9385
9390
9395
9400
9405
9410
9415
9420
9425
9430
9435
9440
9445
9450
9455
9460
9465
9470
9475
9480
9485
9490
9495
9500
9505
9510
9515
9520
9525
9530
9535
9540
9545
9550
9555
9560
9565
9570
9575
9580
9585
9590
9595
9600
9605
9610
9615
9620
9625
9630
9635
9640
9645
9650
9655
9660
9665
9670
9675
9680
9685
9690
9695
9700
9705
9710
9715
9720
9725
9730
9735
9740
9745
9750
9755
9760
9765
9770
9775
9780
9785
9790
9795
9800
9805
9810
9815
9820
9825
9830
9835
9840
9845
9850
9855
9860
9865
9870
9875
9880
9885
9890
9895
9900
9905
9910
9915
9920
9925
9930
9935
9940
9945
9950
9955
9960
9965
9970
9975
9980
9985
9990
9995
10000
10005
10010
10015
10020
10025
10030
10035
10040
10045
10050
10055
10060
10065
10070
10075
10080
10085
10090
10095
10100
10105
10110
10115
10120
10125
10130
10135
10140
10145
10150
10155
10160
10165
10170
10175
10180
10185
10190
10195
10200
10